

# AAM/LP

## Alarm Acknowledgement Module



Intelligent/Addressable Devices

### General

Notifier's Alarm Acknowledgement Module (AAM/LP) is designed for use where regulations and AHJ's permit to assist in the reduction of transmission of unwanted alarms to the Brigade and the general premises.

When an addressable smoke detector activates, the LED indicator and external sounder or sounder base will activate and provided the acknowledge button is depressed within the alarm acknowledgement period the FIP will be inhibited from sending the alarm to the CIE for the alarm investigation period.

This gives the occupant time to investigate the cause of the alarm and, if it is a nuisance alarm e.g. burning the toast, and they are able to clear the cause and allow the system to reset before the expiry of the investigation period no alarm will be sent.

The acknowledgement period and the investigation period can be set via the FIP configuration. If either of these time periods are not met an alarm will be transmitted to the CIE to signal that Fire Brigade dispatch is required and alert the general premises.

During this period should another initiating device in the same occupancy go into alarm this will be instantly transmitted by the FIP to the CIE.



### Features

- Ideal for SOU applications.
- Single gang plate design.
- FMM-101 fitted
- LED indication.
- Momentary-action switch.
- Powered and controlled from the loop.
- Software adjustable timers.

### Approvals

SSL Test Specification FTS-136  
Listed in afp-1156 & afp-1157

## Specifications

Average Operating Current:	375µA maximum (group poll) 350µA maximum (direct poll) 600µA maximum ((Communicating, IDC shortedl)
Dimensions:	74mm x 51mm

## Ordering Information

11808	AAM/LP Alarm Acknowledgement Module - Loop Powered (requires loop powered sounder for AAM operation)
-------	--

---

© 2009 by Honeywell International Inc. All rights reserved.  
Unauthorised use of this document is strictly prohibited.

---

This document is not intended for installation purposes.  
We try to keep our product information up-to-date and accurate.  
We cannot cover all specific applications or anticipate all requirements.  
All specifications are subject to change without notice.

For more information contact your nearest Notifier Sales Office or Distributor  
[www.notifier.com.au](http://www.notifier.com.au)

---